



KANE-RVP6

6 CFM 2-STAGE SPARKLESS BATTERY POWERED VACUUM PUMP



Almost every service technician today has cordless battery powered tools using one of the three major battery platforms: **Makita®**, **Dewalt®**, or **Milwaukee®**. We've designed a **6CFM Battery Vacuum Pump** featuring DC Brushless Motor technology, that includes a battery adapter so all three major battery platforms can power this pump.



Makita® Battery



Milwaukee® Battery



DeWalt® Battery



(Batteries not included)



Included with Pump!
Part# KANE-RVPBA Battery Adapter with USB Port to Charge or Power a Cell Phone or Tablet

For technicians with battery anxiety, particularly in the commercial sector with longer evacuation requirements, there is an AC/DC Power Adapter sold separately. (Part# KANE-RVPPA)

Input:
100 - 240V ~ 50 / 60Hz
Output:
24V - 12A



Part# KANE-RVPPA
AC/DC Adapter
(sold separately)

SPECIFICATIONS

DISPLACEMENT	6 CFM (170L/min)
FACTORY RATED	15 Microns
INTAKE FITTINGS	1/4", (2) 3/8" and 1/2" Male Flare
POWER SUPPLY	Battery 18V to 20V AC/DC Adapter KANE-RVPPA (sold separately)
MOTOR POWER	1/2 HP Brushless DC Motor
OIL CAPACITY	16.9 oz.
DIMENSIONS	13"x 5.1"x 11.4" (33 cm x 13 cm x 29 cm)
WEIGHT	16.5 lbs. (7.5 kg)

U.S. and International Patent Pending

Trademarks: Makita®, LXT®, AVT® and the Makita® logo, Teal color and Black & White color combination are the registered trademarks of Makita®. Dewalt® is a registered trademark of Dewalt Power Tools. Milwaukee® is a registered trademark of Milwaukee Power Tools.

